

APX 6500

SINGLE-BAND P25 MOBILE RADIO



STAY INFORMED. STAY SAFE.

You may not know what the next call will entail, but you do know that your team needs communication they can count on. Whether on a motorcycle, in a squad car or a fire truck, the rugged and compact design of the evolved APX™ 6500 mobile radio is designed to maximize the real estate in your vehicle and keep your entire agency safely connected. Now with integrated Wi-Fi, Bluetooth and SmartConnect, the APX 6500 gives you more ways to manage your radio and stay connected. And when your vehicle sustains a high impact, the radio can automatically alert dispatch.

Security is more important than ever. Criminals are testing you on the streets and over the air. Fight back with multiple levels of protection to encrypt and secure your voice and data communication against eavesdropping.

Stay connected, keep safe and secure your communications with the APX 6500 single-band mobile radio.





GET CONNECTED AND STAY CONNECTED

When the mission takes you out of range, you risk being left in the dark. The APX 6500, equipped with SmartConnect, can reroute P25 voice and data communication over broadband via built-in Wi-Fi or a tethered LTE/satellite router. Stay connected to your P25 radio system, even when outside of P25 coverage.



VOICE AND DATA, ALL AT ONCE

Packed with all the connections you need, the APX 6500 keeps your team in touch and within reach of over-the-air updates. Receive new codeplugs, firmware updates and software features at the speed of Wi-Fi— without interruptions to voice communications.





KEEP VOICE AND DATA PROTECTED

The APX 6500 secures voice and data using multiple hardware encryption algorithms and the ability to rekey over the air, so it's protected from scanners and eavesdroppers. What's more, P25 Radio Authentication ensures only valid users can access the system while the available two-factor authentication secures database logins.



FLEXIBLE, EASY INSTALLATION

The small and light form-factor of the APX 6500 allows for easy installation across a growing ecosystem of vehicles and installations. Users can choose one of several interchangeable control heads to best fit their need. Dual control head configuration enables radio operation from multiple locations within the same vehicle, such as a large fire truck.



ALL THE SUPPORT YOU NEED

From simple support for technical troubleshooting to a complete transfer of optimization and maintenance services to Motorola Solutions, you choose the level of support that suits you best.

02 CONTROL HEAD

EXTREME USABILITY

The O2 control head provides rugged simplicity for efficient and confident communication. Extreme controls with easy to read color display and a built-in 7.5 watt speaker provides clear visual and audible user experiences. Available in high impact green or black.





03 HANDHELD

APX 6500 COMPATIBLE CONTROL HEADS*



Full color display with night mode and intelligent lighting Multi-function channel / volume knob intelligent lighting MOTOROLA APX 6500 SmallConnect Zone Chan Call Next Integrated controls for siren and lights, PA and gunlock or DTMF keypad

E5 CONTROL HEAD

UNMATCHED READABILTY. OPTIMIZED USABILITY.

A bright color display and intelligent lighting makes the E5 easy to read under any condition while the optimized tactility and button placement reduces inadvertent actuations.

07 CONTROL HEAD

INTEGRATED MULTI-FUNCTIONALITY

The O7 is a sophisticated control head with a color display and built-in keypad. It can integrate your radio vehicle control into a single ergonomic interface and supports dual radio installations.



FEATURES

GENERAL FEATURES	
Channel Capacity	1,000 channels standard, expandable to 3,000 channels
Encryption Algorithms	256-bit AES, ADP, DES, DES-XL, DES-OFB, DVP-XL

OPERATING MODES Digital Trunking: 9600 Baud APCO P25 Phase 1 FDMA and Phase 2 TDMA Analog Trunking: 3600 Baud SmartNet®, SmartZone®, Omnilink Digital Conventional: APCO 25 Analog Conventional: Analog MDC 1200, Quik Call II System Configurations

SmartConnect Connectivity

INTEGRATED WI-FI, GPS AND DATA CONNECTIVITY

Wi-Fi 802.11 b/g/n with up to 20 Wi-Fi networks provisioned in the radio¹

Data Modem Tethering¹

ASTRO 25 Integrated Voice and Data

Enhanced Data¹

Integrated GPS/GLONASS for Outdoor Location Tracking

Mission Critical Geofence¹

Personnel Accountability¹

SmartConnect¹

MANAGEMENT	
Customer Programming Software (CPS)	
Radio Management	
Over-the-air Programming (OTAP)1	

SECURITY
Tactical Inhibit ¹
P25 Authentication ¹
Software Key ¹
Single-key ADP Encryption ¹
Multikey for 128 keys and multi-algorithm ¹
Over-the-air Rekeying (OTAR) ¹

GPS/GNSS SPECIFICATION	IS Control of the con
Channels	12
Tracking Sensitivity	-164 dBm
Accuracy ²	<5 meters (95%)
Cold Start ²	<60 seconds (95%)
Hot Start ²	<5 seconds (95%)
Mode of Operation	Autonomous (Non-Assisted) GNSS or SBAS

Bluetooth (Version 4.2)

¹ Optional

 $^{^{\}rm 2}$ Measured conductively with >6 satellites visible at a nominal -130 dBm signal strength

 $[\]ensuremath{^{*}}$ SmartConnect not available in all countries.

Please check with your Motorola Solutions representative for availability in your country.



ENCRYPTION	
Supported Encryption Algorithms	ADP, 256-bit AES, DES, DES-XL, DES-OFB, DVP-XL
Encryption Algorithm Capacity	8
Encryption Keys per Radio	Module capable of storing 1024 keys. Programmable for 128 Common KeY Reference (CKR) or 16 PhysicalIdentifier (PID)
Encryption Frame Re-sync Interval	P25 CAI 300 mSec
Encryption Keying	Key Loader
Synchronization	XL — Counter Addressing OFB — Output Feedback
Vector Generator	National Institute of Standards and Technology (NIST) approved random number generator
Encryption Type	Digital
Key Storage	Tamper protected volatile or non-volatile memory
Key Erasure	Keyboard command and tamper detection
Standards	FIPS 140-3 Level 3, FIPS 197

OTHER FEATURES
Text Messaging
Radio Profiles
Dynamic Zone
Intelligent Priority Scan
Unified Call List
Instant Recall
Data Modem Connection (wired or Wi-Fi) ¹
12 Character RFID Asset Tracking ¹
Digital Tone Signaling ¹

INTEGRATED WI-FI, GPS AND DATA CONNECTIVITY					
Frequency Range/Band splits	WLAN (Wi-Fi): 2412 - 2472 MHz; 5180 - 5320 MHz; 5500 - 5825 MHz				
WLAN (WiFi) 802.11 b/g/n (2.4GHz)	Security protocols	WPA-2, WPA, WEP			
802.11 a/n/ac (5GHz)	SSIDs	Up to 20 pre-provisioned			
Data Modem Tethering ¹					
Bluetooth Version 4.2	2402-2480 MHz Supports MPP Pairing ² and compatible with HSP, PAN, DUN and SPP Profiles found in Off-the-shelf Bluetooth accessories. Supports up to 6 data connections and 1 audio connection.				


SIGNALING (ASTRO 25 MODE)	
Signalling Rate	9.6 kbps
Digital ID Capacity	10,000,000 Conventional / 48,000 Trunking
Digital Network Access Codes	4,096 network site addresses
ASTRO Digital User Group Addresses	4,096 network site addresses
Project 25 – CAI Digital User Group Addresses	65,000 Conventional / 4,094 Trunking
Error Correction Techniques	Golay, BCH, Reed-Solomon codes
Data Access Control	Slotted CSMA: Utilizes infrastructure-sourced data status bits embedded in both voice and data transmissions

¹ Optional ² For E5 Control Head only



DIMENSIONS AND WEIGHT		
Radio Transceiver	51 x 178 x 163 mm (2.0 x 7.0 x 6.4 in)	2.18 kg (4.80 lbs)
Radio Transceiver and O2 Control Head - Dash Mount	69 x 207 x 223 mm (2.7 x 8.1 x 8.8 in)	2.43 kg (5.36 lbs)
Radio Transceiver and O5 Control Head - Dash Mount	51 x 178 x 202 mm (2 x 7 x 8.0 in)	2.24 kg (4.94 lbs)
Radio Transceiver and E5 Control Head - Dash Mount	51 x 178 x 209 mm (2.0 x 7.0 x 8.2 in)	2.24 kg (4.94 lbs)
Radio Transceiver and 07 Control Head - Dash Mount	51x 178 x 208 mm (2 x 7 x 8.2 in)	2.24 kg (4.94 lbs)
Radio Transceiver and Remote Mount	51 x 178 x 193.6 mm (2 x 7 x 7.6 in)	2.18 kg (4.80 lbs)
02 Control Head Remote Mount	68 x 206 x 53 mm (2.7 x 8.1 x 2.1 in)	-
05 Control Head Remote Mount	51 x 180.3 x 64 mm (2.0 x 7.0 x 2.5 in)	-
E5 Control Head Remote Mount	51 x 178.5 x 64 mm (2.0 x 7.0 x 2.5 in)	-
07 Control Head Remote Mount	51 x 178 x 40 mm (2.0 x 7.0 x 1.5 in)	-





PERFORMANCE AND REGULATORY

TRANSMITTER													
		łF		F R1		F R2	700 1			MHz		MHz	
Frequency Range/Bandsplits	136-17		380-470 MHz		450-520 MHz		764-776, 794-806 MHz		806-825, 851-870 MHz		896-902, 935-941 MHz		
Rated RF Output Power (Adjustable)	1-50 1-25			1-40 W 1-25 W ³		1-45 W 1-25 W ³		3-30 W		3-35 W		1-30 W	
Frequency Stability (-30°C to +60°C; +25°C Ref.)	± 0.8	PPM	±0.8	PPM	±0.8 PPM		±0.8 PPM		±0.8 PPM		±0.8 PPM		
Emissions	Conducted -85 dBc	Radiated -10 dBm	Conducted -85 dBc	Radiated -20 dBm	Conducted -85 dBc	Radiated -20 dBm	Conducted -75/-85 dBc	Radiated -20/-40 dBm	Conducted -75 dBc	Radiated -20 dBm	Conducted -70 dBc	Radiated -20 dBm	
Modulation Limiting (12.5/20/25 kHz)	±5/±2	.5 kHz	±5/±2	.5 kHz	±5/±2.5 kHz		±5/±2.5 kHz		±5/±2.5 kHz		±2.5 kHz (12.5kHz only)		
Modulation Fidelity (C4FM) 12.5 kHz Digital Channel	2.5	5%	1.5	0%	1.50%		1.50%		1.5	0%	1.5	0%	
Audio Response	+1, -3 c	IB (EIA)	+1, -3	dB (EIA)	+1, -3 (dB (EIA)	+1, -3 d	B (EIA)	+1, -3	dB (EIA)	+1, -3	dB (EIA)	
FM Hum & Noise (12.5 kHz/25 kHz)	-52 dB /	′-53 dB	-50 dB	/ -53 dB	-50dB ,	/ -53dB	-48 dB /	-50 dB	-48 dB	/ -50 dB	-45 dB (12.5kHz only)		
Audio Distortion (12.5 kHz/25 kHz)	0.5	0%	0.5	0%	0.5	0%	0.50)%	0.5	60%	0.80% (12	.5kHz only)	
RECEIVER													
	VI	łF	UHF R1		UHF R2		700 MHz		800 MHz		900 MHz		
Frequency Range/Bandsplits	136-17	4 MHz	380-470 MHz		450-520 MHz		764-776 MHz		851-870 MHz		935-941 MHz		
Channel Spacing	12.5/2	25 kHz	12.5/25 kHz		12.5/25 kHz		12.5/25 kHz		12.5/25 kHz		12.5 kHz		
Maximum Frequency Separation	Full Ba	ndsplit	Full Bandsplit		Full Bandsplit		Full Bandsplit		Full Bandsplit		Full Bandsplit		
Audio Output Power at Rated/Max	7.5 /	15 W	7.5 / 15 W		7.5 / 15 W		7.5 / 15 W 7.5 / 15 W		15 W	7.5 /	15 W		
Frequency Stability (-30 °C to +60 °C; +25 °C Ref.)	±0.8	PPM	±0.8	PPM	±0.8	PPM	±0.8	PPM	±0.8	PPM	±0.8	PPM	
Analog Sensitivity (12db SINAD)	Pre-Amp -123 dBm (0.158 μV)	Standard -119 dBm (0.251 µV)	Pre-Amp -123 dBm (0.158 μV)	Standard -119 dBm (0.251 µV)	Pre-Amp -123 dBm (0.158 μV)	Standard -119 dBm (0.251 µV)	-121 dB (0).199 µV)	-121 dB ((0.199 μV)	-120 dBm	(0.224 μV)	
5% BER	Pre-Amp -123 dBm (0.158 μV)	Standard -119 dBm (0.251 µV)	Pre-Amp -123 dBm (0.158 μV)	Standard -119 dBm (0.251 µV)	Pre-Amp -123 dBm (0.158 μV)	Standard -119 dBm (0.251 µV)	-121.5 dB	0.188 μV)	-121.5 dB	(0.188 μV)	-121 dBm	(0.199 μV)	
Selectivity (12.5 kHz / 25 kHz / 30 kHz)	77 dB / 89	dB / 90 dB	72 dB /	83 dB / -	72 dB /	83 dB / -	75 dB / 8	85 dB / -	75 dB /	85 dB / -	74 dB (12	.5kHz only)	
Intermodulation Rejection (12.5 kHz / 25 kHz)	Pre-Amp 84 dB	Standard 86 dB	Pre-Amp 82 dB	Standard 86 dB	Pre-Amp 82 dB	Standard 86 dB	82	dB	82	? dB	82	dB	
Spurious Rejection	95	dB	93	dB	93 dB		91 dB		91 dB		91	dB	
FM Hum & Noise (12.5 kHz / 25 kHz)	-50 dB /	/ -59 dB	-50 dB	/ -55 dB	-50 dB ,	/ -55 dB	-50 dB /	-50 dB / -59 dB		/ -59 dB	-50 dB (12	.5kHz only)	
Audio Distortion (12.5 kHz / 25 kHz)	1.2	0%	1.5	0%	1.5	0%	1.20)%	1.2	10%	1.20% (12	.5kHz only)	

POWER AND BATTERY DRAIN						
	VHF	UHF R1	UHF R2	700 MHz	800 MHz	900 MHz
Frequency Range / Bandsplits	136-174 MHz	380-470 MHz	450-520 MHz	764-775, 794-806 MHz	806-825, 851-870 MHz	896-902, 935-941 MHz
RF Power Output	1-50 W 1-25 W ³	1-40 W 1-25 W ³	450-485 MHz: 1-45 W 485-512 MHz: 1-40 W 512-520 MHz: 1-25 W	3-30 W	3-35 W	896-901 MHz: 1-30W 901-902 MHz: 1-3W 935-940 MHz: 1-30W 940-941MHz:1-3W
Operation	13.8 V DC ±20% Negative Ground	13.8 V DC ±20% Negative Ground	13.8 V DC ±20% Negative Ground	13.8 V DC ±20% Negative Ground	13.8 V DC ±20% Negative Ground	13.8 V DC ±20% Negative Ground
Standby at 13.8V	0.85 A	0.85 A	0.85 A	0.85 A	0.85 A	0.85 A
Receive Current at Rated Audio at 13.8V	3.2 A	3.2 A	3.2 A	3.2 A	3.2 A	3.2 A
Transmit Current (A) at Rated Power	8 A @ 15 W 13 A @ 50 W	11 A @ 40 W 8A @ 15 W	11 A @ 40 W 8A @ 15 W	8 A @ 15 W	8 A @ 15 W 12 A @ 35 W	10 A @ 30 W 5 A @ 3 W

 $^{^{\}rm 3}$ 1-25 W applies to countries with a maximum 25W limit.



ENVIRONMENTAL	
Operating Temperature	-30°C/+60°C
Storage Temperature	-40°C/+85°C
Humidity	Per MIL-STD
ESD	IEC 61000-4-2
Water and Dust Intrusion (w/ O2 control head)	IP56, MIL-STD

RADIO MODEL NUMBER	
VHF	M25KSS9PW1BN
UHF R1	M25QSS9PW1BN
UHF R2	M25SSS9PW1BN
700/800	M25URS9PW1BN
800/900	M25VRS9PW1CN

FCC/IC TYPE ACCEPTANCE ID						
FCC/IC ID	Band and Power Level					
FCC ID: AZ492FT7141	896-902MHz (1-30W)					
ISED ID: 109U-92FT7141	935-941MHz (1-30W)					
	764-776 MHz (3-30 W)					
FCC ID: AZ492FT7124 IC ID: 109U-92FT7124	794-806 MHz (3-30 W)					
	806-824 MHz (3-35 W)					
	851-870 MHz (3-35 W)					
FCC ID: AZ492FT7130 IC ID: 109U-92FT7130	136-174 MHz (1-50 W)					
FCC ID: AZ492FT7129 IC ID: 109U-92FT7129	380-470 MHz (1-40 W)					
	450-520 MHz (1-45 W)					
FCC ID: AZ492FT4967 ISED ID: 109U-92FT4967	485-512 MHz (1-40 W)					
	512-520 MHz (1-25 W)					

RED CERTIFICATION	
Designator	Band and Power Level
MMCR308PE	136-174MHz, (1-50W)
MMCR508PE	380-470MHz, (1-40W)

MOBILE MILITARY STANDARDS 810, C, D, E, F, G & H												
	MIL-STD 810C		MIL-STD 810D		MIL-STD 810E		MIL-STD 810F		MIL-STD 810G		MIL-STD 810H	
	Method	Proc./Cat.	Method	Proc./Cat.	Method	Proc./Cat.	Method	Proc./Cat.	Method	Proc./Cat.	Method	Proc./Cat.
Low Pressure	500.1	I	500.2	II	500.3	II	500.4	I/II	500.6	II	500.6	II
High Temperature	501.1	1, 11	501.2	I/A1, II/A1	501.3	I/A1, II/A1	501.4	I/Hot, II/Hot	501.6	I/A1, II/A1	501.7	I/A1, II/A1
Low Temperature	502.1	1	502.2	I/C3, II/C1	502.3	I/C3, II/C1	502.4	I/C3, II/C1	502.6	I/C3, II/C1	502.7	I/C3, II/C1
Temperature Shock	503.1	I	503.2	1/A1C3	503.3	1/A1C3	503.4	1	503.6	I/C	503.7	I/C
Solar Radiation	505.1	II	505.2	1	505.3	I	505.4	1	505.6	I/A1	505.7	I/A1
Rain	506.1	1, 11	506.2	1, 11	506.3	1, 11	506.4	I, III	506.6	I, III	506.6	I, III
Humidity	507.1	II	507.2	II	507.3	II	507.4	-	507.6	II/Aggravated	507.6	II/Aggravated
Salt Fog	509.1	I	509.2	1	509.3	I	509.4	-	509.6	-	509.7	-
Blowing Dust	510.1	I	510.2	1	510.3	I	510.4	1	510.6	I	510.7	1
Blowing Sand	-	-	510.2	II	510.3	II		II	510.6	II	510.7	II
Vibration	514.2	VIII, F, W	514.3	I/10, II/3	514.4	I/10, II/3	514.5	1/24	514.7	1/24	514.8	I/24, II/5
Shock	516.2	I, III, V	516.3	I, V, VI	516.4	I, V, VI	516.5	I, V, VI	516.7	I, V, VI	516.8	I, V, VI



For more information, please visit www.motorolasolutions.com/apx

